
物料编码


物料名称: P200 说明书

尺寸:105x140 MM

材质:80G书纸

工艺:单色双面印刷,折页






Thank you for purchasing our multi-function portable generator. In case of power failure, severe weather

using this unit, please read the user manual carefully and properly keep it for a reference.

**ABOUT THE UNIT** 




Packing included 1 x portable power station; 1 x wall charger; 1 x car charger(Car charger -DC35135); 1 x cigarette il ghter; 1 x instruction manual


非常感谢您使用本公司生产的多功能便携式移动供电储能箱产品。如果遇到停电,或者外出旅行需

# or on the road, you can temporarily charge your electrical or digital devices timely. This power station can provide USB, DC and AC output and keeps your laptops, appliances, lights and more running longer. Before

**PRODUCT PARAMETERS** 



## PRODUCT INSTRUCTION



② Long press the AC control switch button for 3S, the AC indicator on the screen will light up, then connect he power cord of the electrical appliance to the AC power socket, this power station start to power your

Short-circuit/Overload Protection: If the AC output is short-circuited or overloaded (Load power>200W

the generator will turn off the AC output to protect itself. Please solve the problem and plug the AC cable adaptor offered to your AC socket or connect the PD charger to the Type-C port for restart. Note that even if the electrical wattage used is less than 200W, sometimes this product will not work due to sudden excessive current. Even for some electrical appliances with a nominal rated power of 200W, the beak power may exceed 200W, so this machine will turn on the over-power protection. Please remove the ectrical equipment and consult the equipment manufacturer for more information. Then press the AC

outton again to get AC output. **If you don't use the AC port, please turn it off in time to save energy.** You can long press the AC control utton to turn off, or long press the power control button to turn off the entire product.

The AC power socket interface specifications, AC voltage and frequency of this product vary from country to country or region. Please refer to the actual product. Before use, be sure to carefully check whether the specifications of the product are consistent wit those of the electrical appliance, otherwise it may cause dangerous situation! How to provide power for USB smart devices?


2. Connect the standard USB cable of the digital device to the USB interface of this product, and the USB output will provide power for the digital device. Then the USB OUT /Type-C OUT indicator on the screen will light up.

\* The maximum input/output of the Type -C is PD65W, (5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3.25A),

is compatible with smart devices that support PD fast charging agreement, such as mobile phones or tablets. The actual charging voltage and current are related to your smart device used. You can consult the device manufacturer to obtain the corresponding information. This product supports Qualcomm Quick Charge 3.0 output technology. The output supports 5V/2A, 9V/2A 12V/1.5A max and is compatible with smart devices that support Qualcomm Quick Charge 3.0 technology How to use the LED function such as mobile phones or tablets. The actual charging voltage and current are related to your smart device 1. Short press the power button "  $\ddot{\triangledown}$  " to turn on the device, the LED screen lights up and display the used. You can consult the device manufacturer to obtain the corresponding information.

Fig. 1. The USB ports with the intelligent power saving mode. When there are no device connected or the device is fully charged, the USB output will be automatically turned off within 30 seconds; you can also touch and hold the power button to turn it off after the charging.

#### How to power vehicle equipment or devices with DC5521 interface




#### Plug the AC cable adaptor offered to your AC socket, the charging will start. 2. When the battery icon on the screen flashes, it means that the machine is charging and the current po

- level will be displayed. When all the battery icons on the screen are displayed and no longer flashing, it means the product is fu harged. Please unplug the charging adapter from the AC outlet in time.
- ※ Please use a specified charger to charge this product. Note: Please use the attached adapter for charging. Please do not use the adapter if it is damaged.
- During the charging, the adapter will heat up, which is normal. In a confined space, the adapter will

become very hot, please do not use it for a long time. And please do not touch it for a long time to avoid b The cooling fan runs at high speed according to the input power to prevent the inside from heating up. \* During the charging process, it may take some time to fully charge the remaining few percent of the battery. This is the protection for the internal battery status and prevent the battery from overcharging.

## Charged by Solar Panel



1. Place the solar panel toward the sunlight, then connect the power station to the solar panel with the DC35135mm interface cable for charging. 2. When the battery icon flashes on the screen, it means that the machine is charging and will display the

current charging power level. 3. When all the battery icons on the screen are displayed and no longer flashing, it means the product is charged. Please remove the charging cable in time.

During the charging, it may take some time to fully charge the remaining few percent of the battery. This is the protection for the internal battery status and prevent the battery from overcharging. ote that this is the standard charging time under ideal conditions.

naximum input current is 2.5A ; when the input voltage is above 20 and below 28V, the maximum input current s 1A. If the input voltage is greater than 28V, the protection function will automatically start and stop charging. \* When charged from the sunlight, please do not expose the product to the sun in order to avoid

The DC input comes with intelligent protection function. When the input voltage is below 5-20V, the

shortening the product life. If the sunlight is not enough, the charging power will be influenced and the charging time will be

## If the sunlight is not enough, the charging power will be influenced and the charging time will be

## If the sunlight is not enough, the charging power will be influenced and the charging time will be

## If the sunlight is not enough, the charging power will be influenced and the charging time will be

## If the sunlight is not enough, the charging power will be influenced and the charging time will be

## If the sunlight is not enough, the charging power will be influenced and the charging time will be

## If the sunlight is not enough, the charging power will be influenced and the charging time will be

## If the sunlight is not enough, the charging power will be influenced and the charging time will be


## If the sunlight is not enough, the charging power will be influenced and the charging time will be influenced.

## If the sunlight is not enough, the charging power will be influenced and the charging time will be influenced.

## If the sunlight is not enough, the charging power will be influenced and the charging time will be influenced.

## If the sunlight is not enough, the charge is not enough to t prolonged; please do not use solar panels for charging in cloudy or thunderous weather.

## Charged by Car Charger



Plugging car charger into a 12V cigarette lighter(carport) of your car, and plug other end (DC3.5mm iterface) to the product. . When the battery icon flashes on the scre

When all the battery icons on the screen a harged. Please remove the charging cable in time. During the charging process, it may take some time to fully charge the remaining few percent of the his is the protection for the internal battery status and prevent the battery from overcharging.

If the batttery of car is low, the charger will detect that the voltage is too low and cannot be charged



he power station supports 65W PD charging (PD charger sold separately). lease use the charger with PD fast charging.

etc.) to avoid short-circuiting.

spose the unit to direct sunlight.

B, Keep away from high humidity and dusty places.

Children must use this product under adult supervision

7, Do not cover the device with towels, clothing and other item.

4, Do not disassemble or reassemble this unit.

5, Do not drop or hit the product strongly.

9, Disconnect the unit when fully charged

ousehold appliances or digital products.

narging capacity;

10, Use the unit properly to avoid electronic shock

. 将PD充电器连接到如图所示的Type-C端口;

请勿跌落、放置重物或强烈撞击本产品。

. 使用时请勿用毛巾、衣物等物品覆盖本产品。

. 充电时本产品可能会发热。这是正常现象。处理时请小心。

b) 充电时, 为了避免产生干扰, 请尽量远离电视, 收音机等设备;

) 如果长时间未使用本装置,请断开电缆再存放;

) 一些便携设备可能需要设定在充电模式方可充电,

1. 请按照当地规定处理报废产品,不要将内置电池当作生活垃圾处理,以免引起爆炸和污染。

) 本产品内置优质原厂锂离子电池,无记忆效应,大容量,持久耐用。但我们还是建议用户在 10℃~30℃范

2. 产品只做应急电源使用,不可替代家用电器或数码产品等标配直流电源或交流电源。

. 请避免让小孩戏玩本产品。

0. 正常使用本产品,避免触电。

. 充满电后断开电源。

产品使用技巧

国间使用,以获得最佳化充电容量;

Connect the PD charger to the Type-C port as shown in the figure; 2. When the battery icon flashes on the screen, it means that the machine is charging and will show the When all the battery icons on the screen are displayed and no longer flashing, it means the product i fully charged. Please remove the charging cable in time.

※ During the charging process, it may take some time to fully charge the remaining few percent of the battery. This is the protection for the internal battery and prevent the battery from overcharging.

\* During PD charging, it is not recommended to turn on the AC output! PD 65W charging function requires a specific Type-C cable (>65w), you can consult the manufacture obtain the corresponding information. You can charge the power station by the PD charging and AC adaptor. The two ways to supply

1, Do not short-circuit the unit. Please keep the unit away from all metal objects (e.g. coins, hair-pins, key

2. Do not heat or dispose this unit in fire, water or other liquids. Keep away from high temperatures an

11, Please deal with scrap products in accordance with the local regulations, do not treat the built-in bat

2, The product is only used for emergency situations, it cannot replace the standard DC or AC power for

a) This product has built-in high-quality original lithium-ion battery, no memory effect, large capacity and

urable. But we still recommend the user uses it in the temperature of 10°C~30°C to obtain the optimal

lease disconnect the charging cable before storing if you don't use it for a long time; Some portable electronic devices may need to be set in the charging mode before being charged.

k储能电源支持65W PD充电(PD充电器另售)。请使用带有PD快速充电功能的充电器。

. 当屏幕上电池图标闪烁时,表示机器正在充电,并显示当前充电功率;

In order to avoid interference, please try to stay away from TV, radio and other equipment while charging

B, The unit may become hot when charging. This is normal. Please be careful while using.

household garbage, so as not to cause the explosion and pollution.

power at the same time can reduce the charging time of the product. This product is used for home, outdoors and emergency, it can't replace the normal alternating current. For a long-term use, please use the power station with specifications required by the Security and maintenance

#### Use in cold weather

It will help to promote material recycling.

actual, please in kind prevail.

months,when you don't use it for a long time.

**Corrected Sine Wave output** 

Due to the chemical characteristics of the battery, the capacity will be affected on cold weather (Below 0°C If you live in a cold place and cannot use AC power from the grid, we recommend you to store this unit in a temperature-isolated place, and connect to a power source. The heat naturally generated during the charging process will help this product to be in the best capacity as possible.

In order to extend the service life (lithium battery), we suggset you to charge it at least once every 3

This manual is to help you use the power station correctly; it does not represent any descriptions of the

rdware and software configuration of the product. About the product configuration, please refer to the

er manual or consult to the seller. Pictures in this manual are for reference only, if it doesn't match the

his power supply provides improved correction wave output,compatible with AC operating at correctic

 $Please \ send \ used \ electronic \ products, \ batteries \ and \ packaging \ materials \ to \ a \ special \ collection \ place.$ 

## Battery information

is device has a built-in non-removable rechargeable battery. Do not try to remove the battery to avoid damages. The battery can be charged and discharged hundreds of times, but it will eventually die.

Our company provides customers with warranty of 12 months from the date of purchase.

# CE FE ROHS PS

## 为了延长产品(锂电池)的寿命,最好在3个月内充电一次。

本手册的用途在于帮助您正确地使用产品 , 并不代表对本产品的软硬件配置的任何说明。有关产 品的配置情况 ,请查阅与本产品相关的合约 ( 若有 ),或咨询向您出售产品的销售商。本手册中的图 片仅供参考,如果有个别图片与产品实物不符,请以产品实物为准。

本电源提供改进的修正波输出,可与工作在修正波(功率<200W)的交流电器兼容。

## 本品仅作为应急用途,不可用来替代正常家用交流电使用,长期使用电器请务必采用电器所需供电规范


#### 寒冷天气使用

由于电池的化学特性,寒冷的天气(零摄氏度以下)将影响到本机电池的容量。如果您居住在寒冷的地 方且无法使用电网交流电 , 我们建议您将本机储存于隔温的地方, 并且连接到一个电源中 ( 太阳能电池 板 )。本机充电过程中自然产生的热量将帮助本品尽可能处在最佳容量状态。


请务必将废旧的电子产品、电池以及包装材料送交到专门的回收点。


CE FE ROHS PS


## 要用电,您可以使用该产品为您的电器或数码产品供电。本电源支持 USB输出, DC直流电输出, AC交流 电输出,可以为您的笔记本,电器,照明灯进行供电等。使用本产品前,请认真阅读本用户手册,并妥





『J 4种模式(低-中-高-SOS)8W/500LM >500次 † 170\*120\*165MM .作温度 -10~40°C












Type-C输入/输出指示 LED灯指示



## 产品使用说明 如何使用本品为交流电器供电

如何为USB智能设备供电?




①长按电源键"()"3秒开启本设备,LED显示屏亮起显示剩余电量。 ②长按AC控制开关按钮3秒,屏幕上的AC指示灯亮,然后将电器的电源线接到本产品的AC电源插座上。 本设备开始为您的电器设备供电。

※ 短路/过载保护:如果AC输出短路或过载(负载>200W),本设备将自动保护并关闭AC输出。请移除短路 或过载的电器设备后,重新充电激活启动本设备。 ※ 注意:即使使用的电器功率小于200W,有时本产品也会因电流突然过大而无法工作。即使一些额定功率为200W的电器,其峰值功率也可能超过200W。这样机器就会启动过功率保护。请移除电气设备,更

多信息请咨询设备制造商。再次按下AC控制按键,即可重新打开AC交流输出。 ※ **当不使用AC交流接口时,请及时关闭AC输出,节省能源。**您可以长按AC控制按钮关闭,或长按电

本品 AC 电源插座接口规格、AC 交流电电压与频率因不同国家或地区不同,请以实物为准。 使用前务必仔细查看产品的规格是否与电器的使用规格一致, 否则可能导致危险情况!





长按电源键"(I)"3秒开启设备,LED显示屏亮显示剩余电量; 2. 将数字设备的标配USB线连接到本产品的USB接口上,USB输出接口将为数字设备提供充电。这时屏幕 上的USB OUT/Type-C OUT指示灯亮起。

※Type-C最大输入/输出为 PD65W(5V/3A、9V/3A、12V/3A、15V/3A、20V/3.25A),兼容支持PD快速充 **也协议的智能设备,如手机或平板电脑。实际充电电压和电流与您使用的智能设备有关。您可以咨** 询设 备厂商获取相关信息。 ※ 本产品支持高通快充3.0输出技术。输出支持5V/2A、9V/2A、12V/1.5A max,兼容支持高通快充3.0 技术的智能设备,如手机、平板电脑等。实际充电电压和电流与您使用的智能设备有关。您可以咨询设

备厂商获取相关信息。 ※ 本品USB接口具有智能节电模式。当没有设备连接或设备充满电时,USB输出将在30秒内自动关闭;您 也可以在充电完成后按住电源按钮关闭。

## 如何驱动车辆设备或具有DC5521接口的设备?





. 长按电源键" U " 3秒开机,LED显示屏亮起,显示剩余电量; . 短按DC控制开关按钮, 屏幕上DC指示灯亮: 3. 将您的设备/车载充电器线缆的标准5521mm线缆连接到本产品的5521mm端口。本品将为您的设备

※ 5521mm DC端口总输出为10A, 车载充电器插座输出为10A,工作最大输出11A。如果您有任何问题, 我们建议您联系设备的生产厂家,获取相应的信息。

Short press the DC control switch button and the DC OUT indicator on the screen will light up;

female port of this product. This unit will provide power to your device.

The output voltage of the DC/car charger socket of this product is 12V;

 $Connect the standard \, 5521 mm \, cable \, of your \, device/ \, car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, to \, the \, 5521 mm \, port/car \, charger \, cable \, the \, the$ 

The total output of DC5521mm ports is 10A, The output of car charger socket is 10A. The maximum

output is 11A when both are working . If you have any problems, we suggest you to contact manufacturer o

When you don't use the DC ports, please turn it off in time to save energy. You can short press the DC

control button to turn off the DC output, or long press the power control button to turn off the entire produc


2. Short press the LED control switch button, the LED light will come on, and the bulb-shaped indicator or

The LED lighting function has four modes: Low-Medium-High-SOS, switch by short pressing.

《**不使用DC直流端口时,请及时关闭电源,节省能源。**短按DC控制按钮可以关闭直流输出,长按电源 2制按钮可以关闭整个产品。

※ LED照明功能有: 弱-中-强-SOS, 短按电源按键可以切换四种模式。

## 如何为本产品进行充电?




. 当屏幕上所有的电池电量图标都显示并且不再闪烁时,表示产品已充满电。请及时将充电适配器从交流 ※ 请使用指定的适配器给本产品充电。 ※ 请使用附带的适配器充电。

度充电。

※ 本品DC 输出电压为12V;

# 短按LED控制开关按钮"♡",LED灯亮,屏幕上灯泡形状的指示灯亮起。



※ 如果适配器损坏,请不要使用。

请不要长时间触摸,以免烫伤。 ※ 冷却风扇根据输入功率高速运转,防止内部升温。 ※ 充电过程中,可能需要一段时间才能将剩余的少量电量充满。这是对电池内部状态的保护,防止电池过

将提供的交流适配器电缆插入您的交流插座, 充电将开始。

. 当屏幕上的电池图标闪烁时,表示机器正在充电,并显示当前电量。

. 将太阳能板朝向阳光,然后用DC 35135 mm接口线缆将本产品连接到太阳能板上进行充电; . 当屏幕上电池图标闪烁时,表示机器正在充电,并显示当前充电功率; . 当屏幕上所有的电池图标都显示出来并且不再闪烁时,表示产品已充满电。请及时拔掉充电电缆。

※ 在充电过程中,可能需要一段时间才能将剩余的少量电量充满。这是对电池内部状态的保护,防止电池 ※ 连接功率40W以上太阳能板时,充满电大约需要5~6小时(标准)。请注意,这是理想状态下的标准

※ 直流输入具有智能保护功能。当输入电压低于5-20V时,最大输入电流为 2.5A; 当输入电压在20-28V之间 时,最大输入电流为1A。当输入电压大于28V时,保护功能会自动启动和停止充电。 ※ 阳光下充电时,请不要将产品暴露在阳光下,以免缩短产品使用寿命。 ※ 日照不足会影响充电功率,延长充电时间;请不要在阴天或雷雨天气使用太阳能电池板充电

※ 充电时,适配器会发热,这是正常现象。如在密闭空间内,适配器会变得更热,请长时间不要使用。并

1. 将车载充电器插入汽车12V点烟器,将另一端(DC3.5mm接口)插入产品; 2. 当屏幕上电池图标闪烁时,表示机器正在充电,并显示当前充电功率; . 当屏幕上所有的电池图标都显示出来并且不再闪烁时,表示产品已充满电。请及时拔掉充电电缆。

※ 如果汽车电池电量不足, 充电器会检测到电压过低而无法充电。

※ 充电过程中,可能需要一段时间才能将剩余的少量电量充满。这是对内部电池的保护,防止电池过度。 K PD 65W充电功能需要专用的Type-C线(>65w),可咨询厂家获取相应信息。 《您可以通过PD充电和交流适配器给本产品充电。两种方式同时供电可以减少产品的充电时间。

. 请勿让本装置发生短路。请避免将本装置与硬币, 手饰, 钥匙等金属物品一起存放。 . 请勿加热本装置或将其丢置于火中,水中及其它液体中,高温中,包括太阳直晒。 . 请勿将本装置置于高度潮湿,多尘的环境中。 . 请勿碰撞或私自拆装本装置。

※ 充电过程中,可能需要一段时间才能将剩余的少量电量充满。这是对电池内部状态的保护,防止电池: ※ 此功能适用于带12V点烟器插座的车辆,部分车辆无法为此储能电源供电。

使用PD充电器充电

. 当屏幕上所有的电池图标都显示出来并且不再闪烁时,表示产品已充满电。请及时拔掉充电电缆。

# 这样可以帮助防止不受控制的废弃物处理并帮助推动材料回收。

本设备有内置式不可拆卸充电电池。请勿尝试取出电池,以免毁坏设备。电池可以充电、放电数百次以上, 但最终会失效。

我公司为客户提供自购买之日起12个月的质保。

# P200 用户手册